



CIRO LIGHTED LOWER LEG COVERS

Parts Included:

- 1 Left Lighted Lower Leg Cover
- 1 Right Lighted Lower Leg Cover
- 1 Hardware Kit Including:
 - 4 5/16-18 x 2" Shcs
 - 4 5/16" Hi-Collar Split Lock Washers
 - 8 6" Cable Ties
 - 1 Dielectric Grease Packet
 - 2 Y-Harness, Front Turn Signals

Installation Instructions:

1. Park on a level surface and shut off the bike.
2. Remove stock fender bolts and reflectors.



3. Install lower leg cover by pushing it on. Use two 5/16-18 x 2" shcs and two 5/16" lock washers on each side. Install bolts and torque to manufacturers' specifications.

4. Take off acorn nuts and remove turn signal driving light assembly.

5. Plug in the included y-harness. Plug one side into factory turn signal and route wire from **Ciro Lower Leg Cover** up along brake cable to y-harness.



6. Tuck in y-harness and extra wiring. Secure wire to brake line with cable ties. **NOTE:** Repeat steps 2 through 6 on other side.

7. Turn on bike to check function.



WARNING:

This indication alerts you to the fact that ignoring the contents described herein can result in potential serious injury or death if not followed.

CAUTION:

This indication alerts you to the fact that ignoring the contents described herein can or will result in material damage and/or personal injury.

ATTENTION:

This indication alerts you to the fact if you ignore this detail you will affect the performance or functionality of the product.

All **Ciro** products are designed for "easy assembly" and/or "plug and play". We recommend a competent mechanic install our products, using standard mechanical procedures to assure a safe and successful installation.

NOTE:

Ciro products are designed and manufactured under very strict quality control. **Ciro** products are warranted to be free of defects in material and workmanship for 1 (one) year from date of purchase by the consumer.

Ciro will have no obligation if the customer cannot show proof of purchase.

Warranty will not be granted unless the part is properly installed and maintained.

Ciro will not be liable for any consequential and incidental damages, including labor, or non-**Ciro** products.

Please visit our website Ciro3d.com for our complete warranty policy.

CIRO3D.COM